

Note: This datasheet may be out of date. Please download the latest datasheet of BLM18AG102SN1# from the official website of Murata Manufacturing Co., Ltd. ata.com/en-US/products/productdetail?partno=BLM18AG102SN1%23

### BLM18AG102SN1#

"#" indicates a package specification code.

In Production RoHS REACH

< List of part numbers with package codes > BLM18AG102SN1D BLM18AG102SN1J BLM18AG102SN1B





Packaging

D

J

В

#### Packaging Information


Specifications

Bulk(Bag)

180mm Paper Tape

330mm Paper Tape

1	1
Y	



:	Electrode	
	(in mm)	



Other Usage For general

1 of 4

Minimum Order

Quantity

4000

10000

1000

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Attention



Note: This datasheet may be out of date. Please download the latest datasheet of BLM18AG102SN1# from the official website of Murata Manufacturing Co., Ltd. om/en-US/products/productdetail?partno=BLM18AG102SN1%23

#### BLM18AG102SN1#

"#" indicates a package specification code.



The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground. The nickel barrier structure of the external electrodes provides excellent solder heat resistance.

BLM\_Aseries generates an impedance from the relatively low frequencies. Therefore BLM\_Aseries is effective in noise suppression in a wide frequency range (30MHz to several hundred MHz).

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Attention

2 of 4



Note: This datasheet may be out of date. Please download the latest datasheet of BLM18AG102SN1# from the official website of Murata Manufacturing Co., Ltd. http://www.murata.com/en-US/products/productdetail?partno=BLM18AG102SN1%23

### BLM18AG102SN1#

"#" indicates a package specification code.

#### Specifications

Shape	SMD
Size Code (in mm)	1608
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.15mm
Width	0.8mm
Width Tolerance	±0.15mm
Thickness	0.8mm
Thickness Tolerance	±0.15mm
Impedance (at 100MHz)	1000Ω
Impedance (at 100MHz) Tolerance	±25%
Rated Current (at 85°C)	450mA
Rated Current (at 125°C)	450mA
DC Resistance(max.)	0.5Ω
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.005g
Number of Circuit	1

3 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Attention





Note: This datasheet may be out of date. Please download the latest datasheet of BLM18AG102SN1# from the official website of Murata Manufacturing Co., Ltd. com/en-US/products/productdetail?partno=BLM18AG102SN1%23

## BLM18AG102SN1#

"#" indicates a package specification code.

# Product Data





Impedance-Frequency Characteristics

Equivalent Circuit

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



4 of 4